



## TORQUE TABLES

### Series 31 Electric Actuator

Part Number	Speed in Seconds*	Torque	Volts	Amps	Watts
31-082A-4110011	5	80 in-lbs	120 VAC	0.30	6
31-162A-4110011	10	160 in-lbs	120 VAC	0.30	6
31-082A-4110013	5	80 in-lbs	220 VAC	0.15	6
31-162A-4110013	10	160 in-lbs	220 VAC	0.15	6
31-082A-4110007	5	80 in-lbs	24 VDC	0.70	6
31-162A-4110007	10	160 in-lbs	24 VDC	0.70	6
31-082A-4110009	6	80 in-lbs	24 VAC	1.30	6
31-162A-4110009	12	160 in-lbs	24 VAC	1.30	6

\* Speed is for ¼ turn. Speed for VAC actuators is based on 60 Hz. 50 Hz speeds are 12 seconds and 6 seconds.

**Flow Line Controls, Inc.**

P.O. Box 677 · Schriever, LA 70395 · Phone: 985-414-6003 · Toll Free 1-800-815-9226 · Fax 985-414-6072

[www.flowlinecontrols.com](http://www.flowlinecontrols.com)

Doc. No. FLC3104 © 2009 Flow Line